
## INKER & MASOR



### **MODEL APS**

Holiday Detector 800v to 35,000v



#### **DESIGNED WITH SAFETY IN MIND!**

SAFETY FEATURE
DIGITAL VOLTAGE DISPLAY
LED HOLIDAY INDICATOR
ERGONOMIC DESIGN
VOLUME CONTROL

Distributed by

SAFETY HANDLE



Instrument will work only when safety handle is depressed.

www.teststations.com

www.tinker-rasor.com Info@tinker-rasor.com

www.detectron.com



Tinker & Rasor quality is found in our products, our people and our customer service.



# PRODUCT DATA SHEET MODEL APS HOLIDAY DETECTOR

#### **Features:**

- SAFETY SWITCH INSTANT SHUT OFF
- In Operation indicators
- 800v 35000v in one instrument
- Volume adjustment for use in loud environments
- Super Bright visual holiday indicator
- Ergonomic handle and grip
- · Low battery voltage indicator
- Regulated voltage
- Push button operation
- Compatible with Models AP/S1 & AP/S2 accessories (wand, battery, ground cable)

#### **Construction:**

- Rugged design for long life
- Water & Dust Resistant Carrying Case
- · Weather sealed
- · Solid state electronics

#### **Applications:**

- Pipelines and other coated structures
- · Wide variety of coatings materials
- Thin to thick coatings

#### **Specifications:**

- Pulsating DC output voltage
- Low: 800v to 8,000v
- High: 3,500v to 35,000v
- 100v Resolution (Meter)
- +/- 5% Accuracy
- Battery operated (6v)
- 110v AC Charger (220v available)

#### **Dimensions:**

- 2.5" x 21.5" x 2.75" Instrument only
- 5" x 2.5" x 5.5" Battery box

#### **Carrying Case:**

40.5" x 17" x 7" (1028.7 x 431.8 x 177.8 mm) 40 lbs. (18.14kg) Shipping Weight\* \*Weight will vary based upon electrode choices

DELIVERY: Immediately from STOCK

F.O.B. San Bernardino, CA USA

SERVICE: 24-hour Turn-Around

TERMS: Net30 Days, on approval of credit

WARRANTY: 3 Years, parts and labor



Kit Includes:
Instrument
(2) Batteries, w/ Case
Ground Cable
Wand Handle
Inspection Paddle
Carrying Case
Instruction Manual
Letter of Calibration

Electrode (Choose One): Full Circle Spring Electrode for a

Full Circle Spring Electrode for any one pipe diameter between 4" and 36"

Half Circle Spring Electrode for any one pipe, 0.75" and 8"

Silicone-Rubber Brush Electrode with any one width between 2" and 8"

MODEL APS HOLIDAY DETECTOR